



NOTES: (Unless Otherwise Specified)

- 1 RF INPUT CONNECTOR IS SMA, 2.92mm OR 1.85mm FEMALE.
- 2 RF OUTPUT CONNECTOR IS WR-22 OR WR-28 WAVEGUIDE, SQUARE FLANGE.
- 3 ONLY USED ON PACKAGE NUMBERS ENDING IN "D".
- 4 CONNECTOR DIMENSIONS: SMA & 2.92mm FEMALE ARE .38". 1.85mm FEMALE IS .46".

PACKAGE#	DIM "A"	DIM "B"
_F03_22_	.750	.600
_F04_22_	.950	.800
_F05_22_	1.150	1.000
_F06_22_	1.350	1.200
_F07_22_	1.550	1.400
_F08_22_	1.750	1.600
_F09_22_	1.950	1.800
_F10_22_	2.150	2.000
_F11_22_	2.350	2.200
_F12_22_	2.550	2.400
_F13_22_	2.750	2.600
_F14_22_	2.950	2.800
_F15_22_	3.150	3.000

### Case Outline Example

Input RF Connector:	Function:	Output RF Connector Type:
S=SMA	A=Amplifier	22=WR22
K=2.92mm	M=Multiplier	28=WR28
V=1.85mm		SQ. Flange

SF03M22S

Input Connector Type: M=Male F=Female	Bias Pin Configuration: S=Single Bias D=Dual Bias
---	---